



General

| | |
|------------------------|---|
| Input Voltage | USB 5V 2A |
| Standby Current | ≤70mA |
| Alarm Current | ≤300mA |
| Backup Battery | 3.7V/800mah Polymer batteries |
| Charging Time | Battery switch ON, 8H to charge; 12H standby for full charged |
| Wired Siren volume | 120dB (180s to alarm as default) |
| Receiving Frequency | 433MHz (±75KHz) , PT2262/4.7MΩ EV1527/300K |
| Transmitting Frequency | 315MHz (±75KHz) , PT2262/4.7MΩ EV1527/300K |
| Version 4G-E band | B1/B3/B5/B7/B8/B20(LTE-FDD) |
| Version 4G-SA band | B1/B2/B3/B4/B5/B7/B8/B28/B66 |
| Telephone numbers | 6 groups |
| Wireless accessory | 8pcs remote controller; 99pcs detectors |
| Distance | Remote controllers ≤40 meters (in the open distance) Detectors ≤80 meters (in the open distance) |
| Working temperature | -10°C~+50°C |
| PIR Sensor | 2 pics |
| Contact Sensor | 3 pics |

Highlights

- 99 wireless defense zones, 8pcs wireless remote controllers (App shows 50 defense zones at most)
- Can store 6 phone numbers, 3 SMS numbers
- 3 groups of timely arm and disarm
- 10-second automatic message recording
- Support wireless siren (315MHz frequency)
- Program alarm position
- Program the defense zone into immediate, delay, 24hours, doorbell, elder zone, or bypass model
- Remote control in different places
- Low battery alert of the accessories
- Built-in rechargeable battery
- Support 4G and WIFI